

What is claimed is:

1. A method for transferring audio and video signals and power between a remote
5 source and a central processor over a single coaxial cable in an audio/video security
system, comprising:
modulating a carrier signal with an audio signal and a video signal in a camera at
a remote location;
transmitting the carrier signal on the single coaxial cable to an audio/video
10 processor located at a central control location;
receiving and demodulating the carrier signal into an audio component and a
video component in the audio/video processor for display and acoustic
monitoring;
transmitting power from the audio/video processor to the remotely located camera
15 over the single coaxial cable; and
receiving and regulating the power in the remotely located camera for powering
electronic components within the remotely located camera.
2. The method of claim 1, wherein the steps of transmitting the carrier signal and
20 transmitting power over the single coaxial cable are conducted simultaneously.
3. The method of claim 1, further comprising:
combining the power and the modulated carrier in the audio/video processor; and
splitting the power and the modulated carrier in the remotely located camera.
25
4. The method of claim 1, further comprising displaying the video component on a
video monitor and annunciating the audio component on a speaker.
5. The method of claim 1, wherein:
30 the step of receiving and demodulating the carrier signal comprises receiving and
demodulating a plurality of carrier signals into a plurality of audio

components and a plurality of video components in the audio/video processor
for display and acoustic monitoring; and

the step of transmitting power from the audio/video processor comprises
transmitting power from the audio/video processor to a plurality of remotely
located cameras over a plurality of single coaxial cables whereby a single
coaxial cable is connected to each camera.

6. The method of claim 5, further comprising displaying the plurality of video
components sequentially on a video monitor and annunciating the plurality of audio
components sequentially on a speaker.

7. The method of claim 5, further comprising displaying the plurality of video
components simultaneously on a video monitor and annunciating the plurality of audio
components simultaneously on a speaker.

8. The method of claim 1, further comprising selecting the power in the remotely
located camera from a remotely located power supply positioned near the camera.

9. The method of claim 5, further comprising selectively disabling transmitting
power from the audio/video processor to selected cameras.

10. The method of claim 1, wherein the video signal represents a black and white
image.

11. The method of claim 1, wherein the video signal represents a color image.

12. The method of claim 1, wherein:

the step of modulating a carrier signal comprises modulating a carrier signal with
a video signal in a camera at a remote location; and

the step of receiving and demodulating the carrier signal comprises receiving and demodulating the carrier signal into a video component in the audio/video processor for display monitoring.

5 13. The method of claim 5, further comprising:

selecting a remotely located camera having a standard video signal output connected to the audio/video processor and an associated remotely located power supply;

10 disabling the transmitting power from the audio/video processor to the selected remotely located camera over the single coaxial cable; and

receiving the standard video signal from the selected remotely located camera by the audio/video processor for display monitoring.

14. A system for transferring audio and video signals and power between a remote source and a central processor over a single coaxial cable in an audio/video security system, comprising:

means for modulating a carrier signal with an audio signal and a video signal in a camera at a remote location;

15 means for transmitting the carrier signal on the single coaxial cable to an audio/video processor located at a central control location;

20 means for receiving and demodulating the carrier signal into an audio component and a video component in the audio/video processor for display and acoustic monitoring;

25 means for transmitting power from the audio/video processor to the remotely located camera over the single coaxial cable; and

means for receiving and regulating the power in the remotely located camera for powering electronic components within the remotely located camera.

15. The system of claim 14, wherein the means for modulating a carrier signal comprises an audio/video modulator for amplitude modulating the carrier signal with the video signal and frequency modulating the carrier signal with the audio signal.

16. The system of claim 14, wherein the means for demodulating the carrier signal comprises an audio/video demodulator for amplitude demodulating the carrier signal for obtaining the audio component and frequency demodulating the carrier signal for obtaining the video component.

17. The system of claim 14, further comprising means for combining the power and the modulated carrier in the audio/video processor and means for splitting the power and the modulated carrier in the remotely located camera.

18. The system of claim 14, wherein:

the means for receiving and demodulating the carrier signal comprises means for receiving and demodulating a plurality of carrier signals into a plurality of audio components and a plurality of video components in the audio/video processor for display and acoustic monitoring; and

the means for transmitting power from the audio/video processor comprises means for transmitting power from the audio/video processor to a plurality of remotely located cameras over a plurality of single coaxial cables whereby a single coaxial cable is connected to each camera.

19. The systems of claim 14, further comprising a switch in the remotely located camera for selecting the power from a remotely located power supply positioned near the camera.

20. The system of claim 14, wherein:

the means for modulating a carrier signal comprises modulating a carrier signal with a video signal in a camera at a remote location; and

the means for receiving and demodulating the carrier signal comprises receiving and demodulating the carrier signal into a video component in the audio/video processor for display monitoring.

21. The system of claim 18, further comprising:

5 a plurality of switches in the audio/video processor for selecting a remotely located camera having a standard video signal output connected to the audio/video processor and an associated remotely located power supply; means for disabling the transmitting power from the audio/video processor to the selected remotely located camera over the single coaxial cable; and means for receiving the standard video signal from the selected remotely located camera by the audio/video processor for display monitoring.

10 22. A system for transferring audio and video signals and power between a remote source and a central processor over a single coaxial cable in an audio/video security system, comprising:

15 a plurality of remotely located cameras, each camera connected by a single coaxial cable to an audio/video processor at a central control location; a plurality of remotely located microphones, each microphone positioned in close proximity to and electrically connected to a remotely located camera; and the audio/video processor connected to a video monitor and a speaker, in addition to being connected to each of the plurality of cameras by a single coaxial cable.

20

23. The system of claim 22, wherein each camera comprises:

25 a video converter connected to a sender translator video input by a video connection and to a sender translator by a power connection through a switch; an external power supply connector connected to the switch; an external microphone connector connected to the sender translator microphone input; and a coaxial cable connector connected to the sender translator.

24. The system of claim 22, wherein the audio/video processor comprises:

30 a plurality of coaxial connectors connected to a plurality of receiver translators; an audio output from each receiver translator connected to processing circuitry;

a video output from each receiver translator connected to the processing circuitry;
a power supply connected to the processing circuitry, the receiver translators, and
to switches connected to the receiver translators for selectively disabling
power transmission to remotely located cameras and enabling standard video
signals from the selected cameras to be accepted by the processing circuitry;
a video monitor connector connected to the processing circuitry; and
an audio speaker connector connected to the processing circuitry.

25. The system of claim 23, wherein the sender translator comprises:

an audio level adjustment connected between the microphone input and an audio
modulator input of an audio/video modulator;
a video modulation adjustment connected between the video converter input and a
video modulator input of the audio/video modulator;
a voltage regulator with input connected to a splitter power output and output
connected to the audio/video modulator and a video converter power
connection; and
the splitter connected to a coaxial cable connector for connecting to an
audio/video processor, the splitter power output connection connected to the
voltage regulator, and the splitter carrier signal input connected to a mixer
output of the audio/video modulator.

26. The system of claim 25, wherein the audio/video modulator comprises:

the audio modulator input connected to the audio level adjustment and an audio
modulator output connected to a frequency generator;
a frequency generator output connected to a mixer audio input;
the video modulator input connected to the video modulation adjustment and a
video modulator output connected to an input of a video carrier generator;
a video carrier generator output connected to a mixer video input; and
the mixer output connected to the splitter.

27. The system of claim 24, wherein each of the receiver translators comprises:

10016594-10001

5 a connection between a coaxial cable connector and a combiner camera input;
a power input connection between a power input connector, a voltage regulator
input and a combiner power input;
a voltage regulator output connected to an audio/video demodulator;
a filter input connected to a combiner carrier signal output;
a filter output connected to an input of an IF amplifier of the audio/video
demodulator;
an audio output driver having an input connected to the output of a sound detector
of the audio/video demodulator and an output connected to an audio
processing circuitry output; and
10 a video output driver having an input connected to a video output of a video
amplifier of the audio/video demodulator and an output connected to a video
processing circuitry output.

15 28. The system of claim 27, wherein the audio/video demodulator comprises:
an IF amplifier having the input connected to the filter output and an output
connected to an input of a video demodulator;
an output of the video demodulator connected to an input of the video amplifier;
the video output of the video amplifier connected to the input of the video output
20 driver and an audio output of the video amplifier connected to an input of an
IF filter;
an output of the IF filter connected to an input of a sound IF amplifier; and
an output of the sound IF amplifier connected to the sound detector whose output
is connected to the input of the audio output driver.

25 29. The system of claim 24, wherein the processing circuitry generates a video
monitor signal that is sent to the video monitor for sequential display of images from the
plurality of cameras, and generates an audio speaker signal that is sent to the speaker for
sequential annunciation of sound from the plurality of microphones synchronized with
30 the monitor displayed images.

30. The system of claim 24, wherein the processing circuitry generates a video monitor signal that is sent to the video monitor for simultaneous display of images from the plurality of cameras, and generates an audio speaker signal that is sent to the speaker for selected annunciation of sound from one of the plurality of microphones.

5

10016594 103001